

Batterie - Ladegeräte



Schnelle/Langsame Ladung*



Kupferwicklungen



Analogisches Amperemeter



Thermostat



* Nur bei Mod. AGRI

	Enerbox 10 T3	Enerbox 15 T4	Agri 20	Agri 30
Netzspannung	1 PH - 230 V	1 PH - 230 V	1 PH - 230 V	1 PH - 230 V
Frequenz	50/60 Hz	50/60 Hz	50/60 Hz	50/60 Hz
Ladespannung	6/12 V	12/24 V	12/24 V	12/24 V
Leistungsaufnahme			12 V - 0,45 kW 24 V - 0,65 kW	660 W
Netzleistung	6 V - 90 W 12 V - 150 W	12 V - 0,6 W 24 V - 1,1 W		
Effektiver Strom	6 V - 8 A 12 V - 12 A	12 V - 16 A 24 V - 8 A	12 V - 31 A 24 V - 28 A	12 V - 50 A 24 V - 45 A
Durchschnittlicher Strom	6 V - 5,5 A 12 V - 7,5 A	12 V - 10 A 24 V - 5 A	12 V - 20 A 24 V - 18 A	12 V - 32 A 24 V - 29 A
Nennkapazität			150 Ah	210 Ah
Batterien ladbar				
Ladung in 4 Stunden		40 Ah	40 Ah	56 Ah
Ladung in 8 Stunden		80 Ah	80 Ah	112 Ah
Ladung in 15 Stunden		120 Ah	150 Ah	210 Ah
Schaltstufen				
Total		2	2	4
Langsame Ladung		1	1	2
Schnelle Ladung		1	1	2
Schutzsicherungen	ja	ja	ja	ja
Volumen	0,06 m ³	0,06 m ³	0,026 m ³	0,02 m ³
Abmessungen	24 x 22 x 13 cm	24 x 22 x 13 cm	33 x 28 x 21 cm	33 x 28 x 20 cm
Gewicht	3,5 kg	3,8 kg	8,2 kg	10 kg
EAN Code	8004386711507	8004386712009	8004386721001	8004386722008
Artikelnummer	12.010	12.015	12.020	12.030